Discovery Space Square - Black - App Compatible

Ernesto Gismondi



IP20 Regulable:





LUMINARIA

- Potencia (W): **34W**
- Tensión de alimentación: **220-240V**
- Flujo Luminoso (lm): **1955lm**
- CCT: **3000K**
- Efficiency: **41%**
- Efficacy: **57.51lm/W**
- CRI: **90**
- Dimmable Typology: **Push & APP**

Notas

The APP driver can not be controlled by DALI dimming system and viceversa.

ESPECIFICACIONES

Discovery is more and more the perfect synthesis of the values, knowledge, innovative research and know-how of Artemide. The great optoelectronic skills, combined with a thorough culture of design and with technological know-how, produces perfectly transversal and surprising solutions, which translate innovation into the emotion of perception.
Discovery respects the UGR workplace standards in any position in which it is installed.
It breaks away from traditional concepts and preconceived ideas which clearly separate design elements from the more technical performances of systems dedicated specifically to installation in offices and the introduction of colour opens up the way to new applications and scenarios increasingly focused on our well-being and emotions.

CÓDIGO PRODUCTO: 2004030APP

CARACTERíSTICAS

- Código del artículo: **2004030APP**
- Color: **Black**
- Instalación: **Suspensión**
- Material: **Technopolymer, aluminium**
- Serie: **Design Collection**
- Entorno de uso: **Interior**
- diseño: **Ernesto Gismondi**

DIMENSIONES

- Longitud: **cm 97**
- Ancho: **cm 1.7**
- Altura: **cm 97**
- Altura máxima del techo: **cm 247**

FUENTES DE LUZ INCLUIDAS

- Categoría: **Led**
- Numero: **1**
- Potencia (W): **30W**
- Color Tolerance: **MacAdam 3SDCM**
- Service Life: **L90 (6K) 50000h**

We reserve the right to change our product specifications. — March 2022
Please visit www.artemide.com for the latest product information

Artemide

ACCESORIOS

Device for switching and controlling Artemide App products. Max N.3 inputs for external push buttons. Mains power supply required. To be installed inside flush mounting boxes or junction boxes. DV1080APP