

Discovery Space Spot Square - TW - Black

Ernesto Gismondi



IP20 CE TW Regulable:



LUMINARIA

Discovery

- Potencia (W): **44W**
- Tensión de alimentación: **220-240V**
- Flujo Luminoso (lm): **Warm 2579 Cold 2739lm**
- CCT: **2700-6500K**
- Efficiency: **100%**
- Efficacy: **62.25lm/W**
- CRI: **90**
- Dimmable Typology: **APP,Dali**

Vector Spot

- Potencia (W): **25W**
- Tensión de alimentación: **220-240V**
- Flujo Luminoso (lm): **1465lm**
- CCT: **3000K**

ESPECIFICACIONES

Discovery is an unobtrusive, utterly absent and immaterial element. Its volume is only perceived when switched on, thanks to the light that outlines the central emitting surface. The result is a uniform light, ideal for working environments. The company's great optoelectronic skills, combined with a thorough culture of design and with technological know-how, produces a perfectly all-purpose and surprising solution, which translates innovation into emotional perception.
The Discovery square and rectangular versions become Discovery Spot with the inclusion of the Vector Spot projector, designed by Carlotta de Bevilacqua.
It fits into a circular hole recreated in the emitting surface to allow its different orientations.

CÓDIGO PRODUCTO: 2030030APP

CARACTERíSTICAS

- Código del artículo: **2030030APP**
- Color: **Black**
- Instalación: **Suspensión**
- Material: **Technopolymer, aluminium**
- Serie: **Design Collection, 2021 Artemide Collection**
- diseño: **Ernesto Gismondi**

DIMENSIONES

- Longitud: **cm 97**
- Altura: **cm 97**
- Altura máxima del techo: **cm 247**

FUENTES DE LUZ INCLUIDAS

- Categoría: **Led TW**
- Numero: **1**
- Color Tolerance: **MacAdam 3SDCM**
- Service Life: **L90 (6K) 50000h**

We reserve the right to change our product specifications. — March 2022
Please visit www.artemide.com for the latest product information

Artemide

- CRI: **90**
- Dimmable Typology: **APP,Dali**

Notas

The APP driver can not be controlled by DALI dimming system and viceversa.

ACCESORIOS



Device for switching and controlling Artemide App products. Max N.3 inputs for external push buttons. Mains power supply required. To be installed inside flush mounting boxes or junction boxes. DV1080APP